



23 Mitchell Ave  
Thornaby on Tees  
TS17 9DL  
Tel +44 (0)7790 486888

**IMPORTANT: PLEASE READ BEFORE INSTALLATION**

**SAFETY**

- Ensure the mains isolator is switched off at the consumer unit before commencing works. If in doubt consult a qualified electrician.
- Wiring should be installed in accordance with the latest edition of the IET regulations BS7671.
- The total load on the circuit may not exceed the rating of the circuit cable, fuse or MCB once the switchplate is installed.
- EARTH = GREEN/YELLOW
- NEUTRAL = BLUE/pre APR 2004 BLACK
- LIVE = BROWN/pre APR 2004 RED

**GENERAL INSTALLATION**

- 1) Isolate the mains supply from the existing accessory if necessary by switching off at the main consumer unit to prevent electrocution.
- 2) Remove the retaining screws and carefully withdraw accessory from wall box to reveal connections at rear.
- 3) Check that no mains voltage is present within existing accessory by use of 240 volt test-device, disconnect all cables noting their respective connections.
- 4) Bend back top and bottom wall box mounting lugs if present.
- 5) Connect accessory with reference to diagrams shown for each accessory.
- 6) Check all connections thoroughly.
- 7) Mount accessory, taking care not to trap any cables beneath plate fixing screws. Do not over tighten the fixing screws.
- 8) Switch on mains supply at Consumer Unit and check the operation of accessory.

**GENERAL CARE & RECYCLING**

- At the end of their useful life the packaging and product should be recycled in the correct manner. Check your local authorities for details.

The Electrical inserts used on these accessories are manufactured in accordance with the relevant British and European Standards where applicable.

SOCKETS TO BSEN 1363-2  
45A CONNECTION UNIT TO BSEN 5733

