

**Product Code:** UDTAKIT

**Description:** Assistance Alarm Kit



### Part 1: Pull Cord Module

#### General Information

<b>Indication</b>	LED illuminates in red when in alarm state
<b>Buzzer</b>	>80db when in alarm State
<b>Wire Gauge</b>	1.5mm

#### Inputs

<b>Input Type</b>	Ground & 2 live circuits - X1 & X2
<b>Activation Type</b>	Energise with a Normally Open Clean contact
<b>Purpose</b>	Activation and Reset Circuits

#### Construction

<b>Material</b>	Urea Formaldehyde
<b>Fixing</b>	Surface Only
<b>Colour</b>	White

#### Outputs

<b>Number of outputs</b>	2
<b>Output Type</b>	1 Switched Live sharing common ground Separate output for additional sounders
<b>Output Rating</b>	12V/500mA

#### Power

<b>Operating Voltage</b>	100 ~ 230VAC
<b>Consumption</b>	0.2A
<b>Battery Backup</b>	A23 Battery

#### Environment

<b>Ingress Protection</b>	IP20
<b>Dimensions</b>	Single Gang; 87mm x 87mm x 41mm

### Features

Built in Battery Backup with supplied A23 Battery  
Sounder buzzes intermittantly when battery needs replacing  
Anti-Microbial Properties

### Accessories

<b>UDTAPLBM</b>	Assistance Alarm, Power, Light and Buzzer Module
<b>UDTALBM</b>	Assistance Alarm Light and Buzzer Module
<b>UDTAPCM</b>	Assistance Alarm Pull Cord Module
<b>UDTASPC</b>	Assistance Alarm Replacement Pull Cord
<b>UDTAREM</b>	Assistance Alarm Reset Module

### Part 2: Power, Light, and Buzzer Module

<b>Power Supply</b>	12VDC
<b>Power Consumption</b>	0.3W
<b>Indicator</b>	LED illuminates red when in alarm state
<b>Material</b>	Urea Formaldehyde
<b>Colour</b>	White
<b>Pull Cord Length</b>	3 Meters, with 2 triangular bangles
<b>Dimensions</b>	Single gang; 87mm x 87mm x 41mm

### Part 3: Reset Module

<b>Power Supply</b>	12VDC
<b>Power Consumption</b>	0.3W
<b>Indicator</b>	LED illuminates red when in alarm state
<b>Material</b>	Urea Formaldehyde
<b>Colour</b>	White
<b>Buzzer</b>	>80db when in alarm state
<b>Dimensions</b>	Single gang; 87mm x 87mm x 41mm

### Component Supplied

3 x Backboxes  
Installation Bolts  
Disabled sticker  
A23 Battery  
User Manual